

W-ST Wall-mount Multi-candela Strobes

www.boschsecurity.com



BOSCH

Invented for life



- ▶ Sleek modern aesthetics
- ▶ Multiple voltages (12 VDC or 24 VDC)
- ▶ Voltage test points
- ▶ Eight strobe candela options
- ▶ Universal mounting base

The Cooper Wheelock Exceder Series Strobes feature a sleek modern design that incorporates high reliability and high-efficiency optics to minimize current draw. The reduced current draw allows for a greater number of devices on the two-wire notification appliance circuit. This, in combination with eight candela options in one appliance, no tools needed for changing settings, voltage test points, 12 V or 24 V DC operation, the universal mounting base, and multiple mounting options results in a reduced cost of ownership.

These strobes provide eight candela settings. All the switches to change these settings can be set without a tool and are located behind the appliance to prevent tampering.

The separate universal mounting base can be easily mounted to five industry-standard back box types. They can also be pre-wired to allow full testing of the circuit wiring before the appliance is installed and the surface finished. These wall-mounting strobes also feature voltage test points for taking readings with a volt meter for troubleshooting or AHJ inspection.

Certifications and approvals

Cooper Wheelock holds these Listings and Approvals:

Region	Certification	
USA	UL	UUKC: Signaling Appliances and Equipment for the Hearing Impaired (ANSI/UL 1971), UVAV: Visual-signal Appliances for Fire-protective Signaling Systems (ANSI/UL 1638)
	CSFM	see our website

Installation/configuration notes

Compatibility Strobe:

These strobes provide a non-synchronized strobe appliance when connected directly to a Fire Alarm Control Panel (FACP), or provide a synchronized strobe appliance when used in conjunction with an FACP that incorporates the Cooper Notification sync protocol, a Cooper Notification Sync Module, or the Cooper Notification Power Supply. They are designed to flash at 1 flash per second minimum over their Regulated Voltage Range.

**Notice**

Strobes are not designed to be used on coded systems in which the applied voltage is cycled on and off.

Compatible Products

The following Bosch Security Systems, Inc. products are compatible with the Cooper Wheelock Exceder Series Strobes:

Category	Product ID	Product Description
Control Panels	FPA-1000 ¹	Analog Addressable Fire Panels
	FPD-7024 ¹	Conventional or Addressable ² FACP
	D10024A ³	Analog FACP
	D8024 ³	Analog FACP
	D9124 ³	Addressable FACP
	D7024 ³	Conventional or Addressable ² FACP
	D7022 ³	Conventional FACP
Modules	SM-12/24-R	Synchronization module (red)
	DSM-12/24-R	Dual synchronization module (red)
Power Supplies	FPP-RNAC-8A-4C ¹	Remote Notification Appliance Circuit (RNAC) Power Supply
	PS-24-8MC ¹	Power supply with built-in synchronization protocol

¹ These products have built-in Cooper Notification synch protocol.

² When used with a D7039 Multiplex Expansion Module, the FPD-7024 and D7024 become addressable FACP's.

³ For synchronization, use the SM or DSM modules with these control panels.

Mounting Considerations

The Universal Mounting Base supplied with each strobe can be pre-wired. With the supplied Contact Cover in place, the pre-wired circuit can be checked for continuity before the strobes are mounted. The strobes snap onto the pre-installed Universal Mounting Bases with the Contact Covers removed and can be secured to the base with an optional securing screw. The Universal Mounting Base flush mounts on single-gang, double-gang, 4 in. square, 4 in. octal, 3.5 in. octal and 100 mm European-type back boxes.

Wiring Considerations

The wiring terminals on the Universal Mounting Base accept two appliance wires with diameters between 12 AWG and 18 AWG (ISO 4 mm² and 0.75 mm²) at each terminal.

Parts included

Quant.	Component
1	Strobe appliance
1	Universal mounting base
1	Contact cover
1	Hardware pack <ul style="list-style-type: none"> • Two pan head mounting screws • One securing screw
1	Literature – Installation Instructions

Technical specifications**Electrical****Strobe Current Draw****24 V nominal (16.0 V to 33.0 V range)**

Voltage Type	Current Draw
DC/FWR:	15 cd: 57 mA, 15/75 cd: 70 mA, 30 cd: 85 mA, 75 cd: 135 mA, 95 cd: 163 mA, 110 cd: 182 mA, 135 cd: 205 mA, 185 cd: 253 mA

12 V nominal (8.0 V to 17.5 V range)

Voltage Type	Current Draw
DC:	15 cd: 110 mA, 15/75 cd: 140 mA

Voltage (input)

Regulated	Range
12 VDC	8.0 V to 17.5 V
24 VDC or Vrms	16.0 V to 33.0 V

Environmental

Environment:	Indoor, dry
Relative Humidity:	93±2% maximum, non-condensing
Temperature (operating):	+32°F to +120°F (0°C to +49°C)

Mechanical

Candela Ratings ¹ :	15 cd, 15/75 cd ² , 30 cd, 75 cd, 95 cd, 110 cd, 135 cd, or 185 cd
Dimensions:	5.24 in. x 4.58 in. x 2.19 in. (133.1 mm x 116.4 mm x 55.7 mm)
Material:	Molded plastic enclosure incorporating a Xenon flashtube and Lexan lens.

¹ When set for 12 V operation strobe devices are only approved by UL to be set at 15 cd or 15/75 cd and only to be powered by DC not FWR.

² Although this product is UL Listed at 15 cd, it provides 75 cd on axis.

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Ordering information

W-STR Wall-mount Multi-candela Strobe (two-wire, 12/24 V, red)

Rectangular red two-wire strobe that is field-selectable for eight candela options.

Order number **W-STR**

W-STW Wall-mount Multi-candela Strobe (two-wire, 12/24 V, white)

Rectangular white two-wire strobe that is field-selectable for eight candela options.

Order number **W-STW**

Accessories

DSM-12/24-R Dual Synchronization Module (red)

A 12/24 VDC Cooper Wheelock module that synchronizes notification appliances on a single Class A or two Class B circuits.

Order number **DSM-12/24-R**

SM-12/24-R Single Synchronization Module (red)

A 12/24 VDC Cooper Wheelock module that synchronizes notification appliances on Class B alarm circuits.

Not Available.

Order number **SM-12/24-R**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com